

# Update Zee S2 to Mono 5 Manually

**THIS WILL ONLY WORK ON THE HOMETROLLER ZEE S2, NOT THE PI3 IMAGE.**

**THIS PROCEDURE CANNOT BE RUN FROM LINUX TOOLS. HS3 WILL BREAK**

[Backup your system](#) before making any changes in the Linux OS.

Older units will be running some variation between 4.5 and 4.6. Some plug-ins require version 5 or higher. If you purchased your Zee S2 after 07/16/18, you do not need this script. To check, follow steps 1-3, and 8. If you do not feel comfortable running the follow commands, please contact support and we can remote in and do it for you.

- 1) Shutdown HS3 by going to Tools->System->Shutdown HomeSeer
- 2) Download Putty <https://www.chiark.greenend.org.uk/~sgtatham/putty/latest.html> (for Mac or Linux use Terminal) OR connect a monitor and keyboard to your Zee S2 and simply login.
- 3) If using SSH, Connect to the Zee S2 via IP Address located at [find.homeseer.com](http://find.homeseer.com).
- 4) Login with the homeseer account and the system password. (Not your Web User or MyHS password).
- 5) Download the update script using the following command, without quotes "sudo wget [homeseer.com/linux/mono5\\_zees2.sh](http://homeseer.com/linux/mono5_zees2.sh)"
- 6) Run the script by entering "sudo sh mono5\_zees2.sh ". Your Zee light will turn yellow while the script is running. Enter "y" when prompted once. This update may take 10-20 minutes depending on your internet speed.
- 7) The system will automatically reboot and the light will turn green when finished rebooting and update completed.
- 8) After completion connect back to your Zee S2 and run the following command, "mono --version".